

SAFETYSURE RCD PLUGS & ADAPTORS

SafetySure RCD Plugs & Adaptors fully comply with BS 7071 & EN 61543. The RCD Plug & Adaptors are clam packed.

- Suitable for use with all makes of electrical and gardening appliances
- Electrically latched - reset on power loss
- Cuts the power for added protection against electrocution
- Large, clear indicator window, flags red when "on"
- No need to remove from socket to reset unit (M04A-C & M74A-C)



M04A-C



M74A-C



RC DL-C

**GREEN
BROOK**
ELECTRICAL

Tel +44 (0) 1279 772 772
Fax +44 (0) 1279 422 007
www.greenbrook.co.uk



	M04A-C	M74A-C
Product Finish	Grey	Grey
Description	RCD Adaptor	RCD Plug
Product Dimensions	H110 x W55 x D45.5mm	H95 x W51 x D49.9mm
Product weight	151 gms	156 gms
Barcode	5012739640247	5012739640254
Voltage	230V ~ 50Hz	230V ~ 50Hz
Max Operating Current	13A (3A Inductive)	13A (3A Inductive)
Rated Trip Current	30mA	30mA
Typical Trip Speed	<40ms (typical)	<40ms (typical)
RCD Contact Break	Double pole	Double pole
Guarantee	1 Year	1 Year
Responsive to	Pulsating DC earth faults	Pulsating DC earth faults
Certification & Conformity	BS 7071:1992 & EN 61543:1995	BS 7071:1992 & EN 61543:1995